

Era One

2 and 4-channel transmitters with visor clip.

Ideal and sleek design solution to control multi-user systems.



Inti Transmitters

The colorful line of 2-channel miniaturized transmitters, available in six colors. Ideal for multi-user systems.



Self-learning and built-in proximity receiver with 72 bit O-Code encoding. 433.92 MHz rolling code transmitters with management of Identity Codes and Certificates.

Increase security using data processing and recognition systems that increase its degree of security and deliver a threefold reduction in automation response times.

Easy memorization using a transmitter already programmed in the receiver

Model	Description
ON2E/A	Era One Transmitter, 2 channels, 433.92 MHz
ON4E/A	Era One Transmitter, 4 channels, 433.92 MHz
INTI2Y/A	Inti Transmitter, 2 channels, 433.92 MHz, Yellow
INTI2R/A	Inti Transmitter, 2 channels, 433.92 MHz, Red
INTI2L/A	Inti Transmitter, 2 channels, 433.92 MHz, Lilac
INTI2G/A	Inti Transmitter, 2 channels, 433.92 MHz, Green
INTI2B/A	Inti Transmitter, 2 channels, 433.92 MHz, Blue
INTI2/A	Inti Transmitter, 2 channels, 433.92 MHz, Black

Transmitter Technical Specifications

Model	Carrier frequency	Estimated Range	Encoding	Power supply	Battery life	Protection class	Dimensions Weight
ON2E/A ON4E/A	433.92 MHz	Outdoor: 656 ft (200 m) Inside building: 115 ft (35 m)*	O-Code 72 bit; rolling code**	3VDC; type CR2032 lithium battery	2 years (with 10 transmissions per day)	IP40 (use in protected environments)	1.7w x 2.1f x 0.4h inches 0.02 lbs
INTI2/A all colors	433.92 MHz	Outdoor: 492 ft (150 m); Inside building: 98 ft (30 m)*	O-Code 72 bit; rolling code**	3VDC; type CR2032 lithium battery	2 years (with 10 transmissions for day)	IP40 (use in protected environments)	1.2w x 2.2d x 0.3h inches 0.03 lbs

* Transmitter range and receiver reception capacity may be affected by any devices operating on the same frequency in the area.

** Not compatible with European products.



OXI/A Receiver

Multi-channel plug in receiver, compatible with 936, 1050 and XBA3 boards. Advanced features with Era One and Inti Transmitters.

Management: Receivers can receive and memorize up to 1000 codes/transmitters.

Memorization: An unique receiver output can be associated to each transmitter key.

Versatile: Receiver outputs can be customized through board programming to perform several different functions.

These receivers are not compatible with Homelink®



OXI/A Receiver
multi-channel plug in

318N Receiver

2-channel receiver with normally open relay contacts.

Management: Receivers can receive and memorize up to 63 codes/transmitters.

Memorization: An unique receiver output can be associated to each transmitter key.

Versatile: Operating voltage is 12/24V AC/DC

These receivers are not compatible with Homelink®



318N
Universal receiver

Code	Description
OXI/A	Receiver; 4 channels, 433.92 MHz, 1000 code memory
318N	Receiver, 2 channels, 433.92 MHz, 63 code memory

Receiver Technical Specifications

Model	Reception frequency	Decoding	Number of channels	Power supply	Absorption	Relay contact	Dimensions
318N	433.92 MHz	Digital 52 bit	2	12 - 24V AC/DC	15 mA	Normally Open	3.8w x 1.6d x 0.9h inch
OXI/A	433.92 MHz	Digital 52 Bit	15 - 1050/XBA3 board 2 - 936 board	n/a	30 mA (max)	--	1.9w x 0.7d x 1.7h inch

SYSTEM DESIGN SUPPORT: Contact Nice/HySecurity for CAD drawings, tech manuals, help with custom site requirements or other specifications support. Call to speak with a Nice/HySecurity representative today.

VISIT WWW.NICEFORYOU.US OR WWW.HYSECURITY.COM for specifications, installation manuals, wiring diagrams, parts diagrams, image gallery, videos, training and much more.

Distributed by:



Contact Nice/HySecurity Regional Sales Manager for an operator/parts distributor near you.
 phone **210-545-2900** | **800-226-0178** | www.niceforyou.us | orders@niceforyou.com
 phone **253-867-3700** | **800-321-9947** | www.hysecurity.com | orders@hysecurity.com